

Xtrons PX71AA4DAB 7" Windows CE 6.0 system Double din DAB radio for Audi with CANbus Bluetooth GPS Navigation 3G

<i>Specifications</i>	
Model	PX71AA4DAB
Hardware	MASTAR 2531 800MHZ
Operation System	Window CE 6.0
Applicable Models & Years	Audi A4 (2002-2007)/ S4/RS4/ 8E/ 8F/B9/B7/Seat Exeo (2009-2012)
Highlight	High-end &Elegant Champagne Ultimate Titanium user Interface Design Supports DAB+ Turner Dual Channel CANbus Efficient Heat Dissipation Supports Phonebook contacts search
General	
Power Requirement	10-16V DC
Load Impedance	4 Ω
Max. Power output	16V/4*50W
Tone Control	+/-12dB (Bass:100 Hz, Treble:10 KHz)
Dimensions	Head Unit: 148*178*100mm Face Panel: 235*19*130mm Box: 305*255*175mm
Weight	1.9 KG
Screen Type	Resistive Touch screen, Digital TFT Screen
Screen Size	7"
Button Light	Red
Screen Resolution	800*480
Heat sink	9mm
Language	
Menu Language	Simplified Chinese, Traditional Chinese, English, Russian, Portuguese, French, Spanish, Turkish, Arabic, German, Hebrew, Japanese, Thai, Indonesia
DVD	
Region Free DVD Player	YES
Disc Played	DVD, SVCD, VCD, DVD-5, CD, CD-R, CD-RW, DVD-9, DVD±R, DVD±RW
Video	
Video System	NTSC, PAL
Aspect Ratio	4:3 box mode / 4:3 panorama mode\16:9
Video Output Level	1.0 Vp
Horizontal Resolution	800*480
Audio	
Max. Output Level	1.5V
Frequency Response	20 Hz-20 KHz
Signal to noise ratio	85 Db
Separation	80 Db
Sound Mode	POP, Rock, Jazz, Classical, User, Hall, Cinema
USB & SD	
Maximum Capacity	32GB(the max files in the USB & SD card should be within 4GB)
Audio Files	MP3 WMA WAV AAC
Video File	DAT, DIVX, MPEG, RMVB, VOB, XVID, MP4, AVI, 3GP
Picture File	JPG

AM Tuner	
Tuning Range	Europe: AM: 522 KHZ~1620 KHZ Japan: AM: 522 KHZ~1620 KHZ South America 1: AM: 530 KHZ~1720 KHZ North America 2: AM: 530 KHZ~1710 KHZ Russia: AM: 520 KHZ~1620 KHZ
IF Frequency	450 KHZ
Effective Sensitivity(-30db)	30dB
FM Tuner	
Frequency Range	Europe: FM: 87.5 MHZ~108MHZ Japan: FM: 76MHZ~90MHZ Russia: FM1: 65 MHZ~74 MHZ, FM2: 87.5 MHZ~108MHZ Brazil: FM:520 KHZ~1720 KHZ North America : FM: 87.5 MHZ~107.9 MHZ South America: FM: 87.5 MHZ~108MHZ
IF Frequency	10.7 MHz
Effective Sensitivity (-20db)	7dB
Signal to Noise Ratio	60 dB
Stereo Separation	35dB (1 KHz)
Frequency Response	30-15000Hz
Accessories	2X ISO Wiring Harness 1X USB Cable 1X Remote Control 1X GPS Antenna 2X RCA Cables 1X DAB+ Antenna 4X Disassemble Keys 1X User Manual 1X Radio Antenna 1X CANbus Box 1X Stylus